



## STOP LIGHT SWITCH

### INSPECTION

#### 1. INSPECT STOP LIGHT SWITCH

(a) Check the resistance.

- (1) Measure the resistance using an ohmmeter, and check the results in accordance with the value(s) in the table below.

#### Standard

Tester Connection	Condition	Specified Condition
1-2	Switch pin free	Below 1 $\Omega$
3-4	Switch pin free	10 k $\Omega$ or higher
1-2	Switch pin pushed in	10 k $\Omega$ or higher
3-4	Switch pin pushed in	Below 1 $\Omega$

If the result is not as specified, replace the stop light switch assembly.